



## FBs-40MA/MC

Specification			FBs-40MAR FBs-40MBR	FBs-40MAT/J FBs-40MBT/J
Digital Input	24VDC	High speed (100KHZ)	2 points	
		Medium speed (20KHZ)	6 points	
		Medium speed (Total 5KHZ)	8 points	
Digital output	Relay		16 points	—
	Transistor	High speed (100KHZ)	—	2 points
		Medium speed (20KHZ)	—	6 points
		Low speed	—	8 points
Communication Port	Built-in	1 port (Port0, USB or RS232)		
	Expandable	2 ports (Port1~2, RS485 or RS232 or Ethernet)		
Calendar			optional	
Built-in power supply			SPW24-AC/D12/D24	
Dimension			7.62mm fixed terminal block	

Specification			FBs-40MCR	FBs-40MCT/J
Digital Input	24VDC	High speed (200KHz)	6 points	
		Medium speed (20KHz)	2 points	
		Medium speed (Total 5KHz)	8 points	
		Medium low speed (0.47ms)	8 points	
Digital output	Relay		16 points	—
	Transistor	High speed (200KHz)	—	6 points
		Medium speed (20KHz)	—	2 points
		Low speed	—	8 points
Communication Port	Built-in	1 port (Port0, USB or RS232)		
	Expandable	4 ports (Port1~4, RS485 or RS232 or Ethernet or GSM or ZigBee)		
Calendar			Built-in	
Built-in power supply			SPW24-AC/D12/D24	
Wiring mechanism			7.62mm detachable terminal block	