



## FBs-6NTC

Specification	FBs-6NTC
Number of input points	6 points
Sensor type and temperature measurement range	NTC sensor 10 K $\Omega$ at 25°C, B optional -20~100°C
Temperature Compensation	—
Resolution	0.1°C
Temperature refresh time	2 or 4 seconds
Overall Precision	$\pm 1\%$ of full scale at 25°C
Isolation method	Transformer(power) and photocouple(signal) isolation, 500VAC, 1 minute, no isolation between each channel
Power consumption	24VDC -15%/+20%, 2W max.
Wiring mechanism	7.62 mm fixed terminal block