



## FBs-CBCAN

Specification	FBs-CBCAN
Communication standard	CAN 2.0A CANopen
Network topology	3-Phase fieldbus
Communication speed	10K / 20K / 50K / 125K / 250K / 500K / 1Mbps
Maximum number of connection station	127 stations
Method of sending signal	Event or cyclic transmission
Isolation method	Photocouple (signal) isolation, 500VAC, 1 minute
Number of PDO communication	RXPDO-10, TXPDO-10 total up to 80 registers
Number of SDO channels	Client -1, Server-1
Error control	Heartbeat
Wiring mechanism	3-pin spring terminal block
ID setup method	Same as PLC station number or setup by software
Working mode	Master or slave dual modes